

Chrysler, Force Sears & Gamefisher Application Charts

HP	Year	Model/Serial No.	Ign. Pack	Stator	Trigger	Rect/Reg	Ign. Coil	Harness
3.5	80	32HOD	Magneto	Magneto	Points	-	185-2370	-
3.5	81-84	32H1D/E/H/G	Magneto	Magneto	Points	-	185-2370	-
3.6	74-76	32BC/HC/33BC/HC	Magneto	Magneto	Points	-	RF12211*	-
4	76-84	ALL	Magneto	Magneto	Points	-	185-2370	-
4	84-87	Manual Start	Magneto	Magneto	Points	-	185-2370	-
4.9	75-76	ALL	Magneto	Magneto	Points	-	RF12348*	-
5	92-98	0E000001-0E344999	SEMS (BIM II)	Magneto	In CD	-	300-850899T	-
5	84-89	88A, 88B, 89A	Magneto	Magneto	Points	-	185-2370	-
5	89-92	89B	Magneto	Magneto	Points	-	185-2370	-
5	75-76	ALL	Magneto	Magneto	Points	-	RF12348*	-
6	75-82	ALL	Magneto	Magneto	Points	-	185-2370	-
7.5	72	BOC/B1D/HOC/H1D	116-5475	R525301*	R529029*	-	-	-
7.5	77	BOC/B1C/HOC/H1C	116-5475	R525301*	R529029*	-	-	-
7.5	79-84	All Models	116-5475	R525301*	R529029*	-	-	-
7.5	85	72F5A	116-5475	RF525301*	RF525029*	-	In CD	-
8	78	ALL	116-5475	R525301*	R529029*	-	-	-
8	82	82H8J/87H8A	116-5475	R525301*	R529029*	-	-	-
8	76-77	ALL	Magneto	Magneto	Points	-	185-2370	-
8	79	ALL	Magneto	Magneto	Points	-	185-2370	-
9.9	79-84	Electric Start	116-0301	510095	R510029*	152-9209	-	-
9.9	89-92	89B-91A/91B-92B	116-2379K 2	-	In CD	-	116-2379K 2	-
9.9	89-92	0E000001-0E034999	116-2379K 2	-	In CD	-	116-2379K 2	-
9.9	79-84	Manual Start	Magneto	Magneto	Points	-	185-2370	-
9.9	84-89	84A-89A	Magneto	Magneto	Points	-	185-2370	-
10	76-78	W/CD-Alternator	116-0301	510095	R510029*	152-9209	-	-
10	76-78	Manual Start	Magneto	Magneto	Points	-	185-2370	-
12	76-84	Electric Start	116-0301	510095	R510029*	152-9209	-	-
12	76-84	Manual Start	Magneto	Magneto	Points	-	185-2370	-
15	76-84	Electric Start	116-0301	510095	R510029*	152-9209	-	-
15	92-98	0E035000-0E344999	SEMS (BIM II)	Magneto	In CD	-	300-850899T	-
15	88-92	88A-92A	116-2379K 2	-	In CD	-	116-2379K 2	-
15	88-92	0E000001-0E034999	116-2379K 2	-	In CD	-	116-2379K 2	-
15	76-84	Manual Start	Magneto	Magneto	Points	-	185-2370	-
15	84-87	84A-87A	Magneto	Magneto	Points	-	185-2370	-
20	75-82	Manual Start	Magneto	Magneto	Points	-	185-2370	-
20	75-82	Electric Start	116-0301	510095	R510029*	152-9209	-	R529744*
25	83-84	Electric Start	116-9301	529095	R529029*	152-9209	-	-
25	96-98	0E127700-0E344999	SEMS (BIM II)	Magneto	In CD	-	300-850899T	-
25	89	All Models	116-9301	F525095	RF525029*	152-9209	F510475	-
25	75-82	Manual Start	Magneto	Magneto	Points	-	185-2370	-
25	75-82	Electric Start	116-0301	510095	R510029*	152-9209	-	R529744*
30	79	Manual Start	Magneto	Magneto	Points	-	185-2370	-
30	80-82	Electric Start	116-9301	529095	R529029*	152-9209	-	R529744*
35	76-82	Manual Start	Magneto	Magneto	Points	-	185-2370	-
35	74-75	Manual Start	Magneto	Magneto	Points	-	RF12057*	-
35	74-77	Electric Start	115-3301	R466095*	Points	155-1450	-	R311744-1*
35	78	W/CD-Alternator	116-9301	529095	R529029*	152-9209	-	R529744*

* Premier Services Availability Only (a) Use Condenser P/N 994-4463

Chrysler, Force, Sears & Gamefisher Application Charts

HP	Year	Model/Serial No.	Ign. Pack	Stator	Trigger	Rect/Reg	Ign. Coil	Harness
35	83-84	W/CD-Alternator	116-9301	529095	R529029*	152-9209	-	R529744*
35	87-91	All Models	116-9301	529095	R529029*	152-9209	510475	R529744*
40	92-95	1992-C	114-4952	174-8778K1	134-9527-2	194-5279	339-7370A23	R821620A1*
40	92-95	0E000001-0E138599	114-4952	174-9710K1	134-9527-2	194-5279	339-7370A23	R84-818952A1*
40	96-97	0E138600-0E287999	114-7509	174-2075K2	134-5744-2	194-5279	In CD	R84-828296A1*
40	98-99	0E28800-0E369299	114-7509	174-2075K2	134-5744-2	194-5279	In CD	R84-828296A1*
45	74-78	Manual Start	Magneto	Magneto	Points	-	RF12057*	-
45	76-84	W/Points	-	R466095*	Points	155-1450	-	R311744-2*
45	74-78	MagnaPower	R345301	R466095*	Points	155-1450	182-5475	R344744-1*
50	81-83	W/Points	-	R466095*	Points	155-1450	-	R311744-2*
50	87	B	115-3301	R466095*	Points	152-9209	380475	R658744*
50	84-87	A, C	116-8475	176-3095	136-8029-2	152-9209	In CD	R658744*
50	88	A, B, C	116-8475	176-3095	136-8029-2	152-9209	In CD	R658744*
50	88	D	116-8301	176-3095	136-4029-2	152-9209	182-4475R	R658744-1*
50	89-92	All Models	116-8301	176-3095	136-4029-2	152-9209	182-4475R	R662744*
50	92-95	0E009500-0E138599	114-4952	174-9710K1	134-9527-2	194-5279	339-7370A23	R84-818952A1*
50	96-97	0E138600-0E283999	114-7509	174-2075K2	134-5744-2	194-5279	In CD	R84-828296A1*
50	92	0E000001-0E009499	114-4952	174-8778K1	134-9527-2	194-5279	339-7370A23	R84-921620A1*
55	81-83	All Models	116-5301	176-5095	136-4029-2	155-1450	182-4475R	R475744*
60	84	All Models	116-5301	176-5095	136-4029-2	155-1450	182-4475R	R475744*
60	84-85	All Models	116-5301	176-5095	136-5029-2	155-1450	182-4475R	R475744*
70	79-80	MagnaPower	115-3301	R85095-2*	135-4048	152-9209	182-5475	R438744-1*
70	91-92	E000001-E009499	114-7778	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-817459A1*
70	91-92	E000001-E009499	114-7778	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-817459A1*
70	93-94	E009500-E093699	114-4953	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-823392A1*
70	93-94	E009500-E093699	114-4953	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-823392A1*
70	94-95	E093700-E138599	114-4953	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-827244A1*
70	94-95	E093700-E138599	114-4953	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-827244A1*
75	75-84	MagnaPower	115-3301	R85095-2*	135-4048	152-9209	182-5475	R438744-1*
75	96-99	E138600-0E369299	114-7509	174-2075K1	134-8302-3	194-5279	In CD	R84-828297A1*
75	96-99	E138600-0E369299	114-7509	174-2075K2	134-8302-3	194-5279	In CD	R84-828297A1*
80	77-84	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
80	83-84	W/CD-Alternator	116-5301	176-5095	136-6029-3	155-1450	182-4475R	R615744*
85	83-85	All Models	116-5301	176-5095	136-6029-3	152-9209	182-4475R	R615744*
85	86	A, L	116-5301	176-5095	136-6029-3	152-9209	182-4475R	R615744*
85	87-88	All Models	116-3301	176-3095	136-3029-3	152-9209	182-4475R	R653744*
85	89	B, C, D, E, F, G, H	116-8301	176-3095	136-3029-3	152-9209	182-4475R	R653744*
85	86	B, C, M, N	116-3301	176-3095	136-6029-3	152-9209	182-4475R	R653744*
85	89	L Drive	116-8301	176-3095	136-3029-3	155-1450	182-4475R	R695744*
90	74-77	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
90	83-84	W/CD-Alternator	116-5301	176-5095	136-5029-4	155-1450	182-4475R	R615744*
90	91	A, C, E	116-8301	176-3095	136-3029-3	155-1450	182-4475	R653744-1*
90	90	All Models	116-8301	176-3095	136-3029-3	152-9209	182-4475R	R653744-1*
90	90	L Drive A	116-8301	176-3095	136-3029-3	155-1450	182-4475R	R695744*
90	91	L Drive B & D	114-7778	174-8778K1	134-7029-3	194-5279	339-7370A23	R722744*
90	91	L Drive B & D	114-7778	174-9710K1	134-7029-3	194-5279	339-7370A23	R722744*
90	90	L Drive C	116-8301	176-3095	136-3029-3	155-1450	182-4475R	R723744*

* Premier Services Availability Only (a) Use Condensor P/N 994-4463

Chrysler, Force Sears & Gamefisher Application Charts

HP	Year	Mdel/Serial No.	Ign. Pack	Stator	Trigger	Rect/Reg	Ign. Coil	Harness
90	91	D	114-7778	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-817459A1*
90	91	D	114-7778	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-817459A1*
90	91	E000001-E009499	114-7778	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-817459A1*
90	91	E000001-E009499	114-7778	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-817459A1*
90	91	E009500-E039023	114-7778	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-823392A1
90	91	E009500-E039023	114-7778	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-823392A1
90	92-94	E039024-E093699	114-4953	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-823392A1*
90	92-94	E039024-E093699	114-4953	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-823392A1*
90	95	E093700-E138599	114-4953	174-8778K1	134-7029-3	194-5279	339-7370A23	R84-827244A1*
90	95	E093700-E138599	114-4953	174-9710K1	134-7029-3	194-5279	339-7370A23	R84-827244A1*
90	96-99	E138600-E369299	114-7509	174-2075K1	134-8302-3	194-5279	-	R84-828297A1*
90	96-99	E138600-E369299	114-7509	174-2075K2	134-8302-3	194-5279	-	R84-828297A1*
100	79-84	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
105	76	HB/BF/HF	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
105	77-78	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
105	82-83	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
115	77-82	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
115	83-84	W/CD-Alternator	116-5301	176-5095	136-5029-4	155-1450	182-4475R	R615744*
120	76	BF/HF	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
120	77	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
120	90	L Drive A, B, C	116-8301	176-3095	136-4029-4	155-1450	182-4475R	R653744*
120	90-91	E000001-E0006550	116-8301	176-3095	136-4029-4	155-1450	182-4475R	R653744-1*
120	91-92	L Drive B, D	114-5772	174-8778K1	134-7029-4	194-5279	339-7370A23	R722744*
120	91-92	L Drive B, D	114-5772	174-9710K1	134-7029-4	194-5279	339-7370A23	R722744*
120	92-95	E006551-E139599	114-5772	174-2075K1	134-7029-4	194-5279	339-7370A23	R827244A1*
120	92-95	E006551-E139599	114-5772	174-2075K2	134-7029-4	194-5279	339-7370A23	R827244A1*
120	96-99	E138600-E369299	114-7509	174-2075K1	134-8303-4	194-5279	-	R84-828297A1*
120	96-99	E138600-E369299	114-7509	174-2075K2	134-8303-4	194-5279	-	R84-828297A1*
125	83-84	All Models	116-5301	176-5095	136-5029-4	152-9209	182-4475R	R615744*
125	81-82	W/CD-Alternator	116-5301	176-5095	136-5029-4	155-1450	182-4475R	R615744*
125	85	All Models	116-5301	176-5095	136-5029-4	152-9209	182-4475R	R616744*
125	86	A	116-5301	176-5095	136-5029-4	152-9209	182-4475R	R616744*
125	86	B	116-3301	176-3095	136-4029-4	152-9209	182-4475R	R653744*
125	87-88	A, B, C	116-3301	176-3095	136-4029-4	152-9209	182-4475R	R653744*
125	88	C	116-8301	176-3095	136-4029-4	152-9209	182-4475R	R653744*
125	89	A, B, C, D, E	116-8301	176-3095	136-4029-4	152-9209	182-4475R	R653744*
125	89	L Drive A, B, C	116-8301	176-3095	136-4029-4	155-1450	182-4475R	R695744*
135	76	BF/HF	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
135	77	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
140	78-84	MagnaPower	115-3301	RF85095-2*	135-4048	152-9209	182-5475	R438744-1*
150	89-90	89A, 90C	116-8301	176-3095	136-4029-5	155-1450	182-4475R	R694744-2*
150	90-91	90D, 91A	116-8301	176-3095	136-4029-5	155-1450	182-4475R	R721744*
150	91-92	91B/C/D/F/J-92A/C	116-7323	174-6231K2	136-7029-5	194-5279	339-7370A23	R84-817459A1*
150	91-92	91B/C/D/F/J-92A/C	116-7323	176-4796K1	136-7029-5	194-5279	339-7370A23	R84-817459A1*
150	91-92	E000001-E009499	116-7323	174-6231K2	136-7029-5	194-5279	339-7370A23	R84-817459A1*
150	91-92	E000001-E009499	116-7323	176-4796K1	136-7029-5	194-5279	339-7370A23	R84-817459A1*

* Premier Services Availability Only (a) Use Condensor P/N 994-4463