

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rec./Reg.	Harness
2	-	1	90-06	0T884302-UP	R8203034T*	R823030 1*	Self	-	-
2.5	-	1	90-06	0A855097-UP	R8203034T*	R823030 1*	Self	-	-
3	-	1	90-06	0A855097-UP	R8203034T*	R823030 1*	Self	-	-
3.3	-	1	90-06	0T884302-UP	R8203034T*	R823030 1*	Self	-	-
4	-	1	70-71	2498136-3296136	IN STATOR	174-3996	POINTS	-	-
4	40	1	72-75	3296137-4107219	R336-4516*(a)	174-4469LS 174-4470 HS	POINTS	-	-
4	40	2	76-80	5589202-5595531	114-6222	174-6120K 1	-	-	-
4	-	2	80-89	5595532-A855096	R336-4516*	174-4469LS 174-4470 HS	POINTS	-	-
4.5	-	2	75-80	4107220-5595531	R336-4516*	174-4469LS 174-4470 HS	POINTS	-	-
6	-	2	86-96	0A197112-0G289100	114-7452K1	174-6617K 1	R98450A10*	-	-
6	-	2	97-05	0G760300-0G800999	114-5713	174-5721(b)	R98450A10*	-	R84-12334A 4*
7.5	75	2	70-71	2810637-3274632	IN STATOR	174-3996	POINTS	-	-
7.5	75	2	72-73	3274633-3801457	R336-4516*	174-4469LS 174-4470 HS	POINTS	-	-
7.5	75	2	74-86	3801458-A197111	114-6222	174-6120K1	R338-5286A 6	154-6770	-
8	-	2	86-96	0A197112-0G289100	114-7452K1	174-6617K 1	R98450A5*	-	-
8	-	2	97-05	0G760300-0G800999	114-5713	174-5721(b)	R98450A10*	-	R84-12334A 4*
9.8	110	2	66-71	1865779-3263262	IN STATOR	174-3996	POINTS	-	-
9.8	110	2	72-73	3263263-3795658	R336-4516*	174-4469LS 174-4470 HS	POINTS	-	-
9.8	110	2	74-78	3795659-5206549	114-6222	174-6120K1	338-7283A2	154-6770	-
9.8	-	2	79-85	5206550-6620196	114-6222	174-6120K1	338-7283A2	-	-
9.9	-	2	86-96	0A197112-0G289100	114-7452K1	174-6617K 1	R98450A5*	-	-
9.9	-	2	97-05	0G760300-0G800999	114-5713	174-5721	R98450A10*	-	R84-12334A 4*
10	-	2	86-96	0A197112-0G289100	114-7452K1	174-6617K 1	R98450A10*	-	-
10	-	2	97-05	0G760300-0G800999	114-5713	174-5721(b)	R98450A10*	-	R84-12334A 4*
15	-	2	88-97	0A197112-0G760299	114-7452K 1	174-6617K 1	R98450A10*	-	-
15	XD/S15	2	94-96	0G044365-0G437999	114-4952A30	174-6617A17	R98450A10*	154-6770	-
15	XD/S15	2	96-97	0G438000-0G760299	114-7452K1	174-6617K 1	R98450A10*	154-6770	-
15	Sea Pro	2	96-97	0G438000-0G760299	114-7452K1	174-6617K 1	R98450A10*	154-6770	-
15	Comm	2	97-06	0G760300-0G800999	114-5713	174-5721(b)	R98450A10*	154-6770	R84-12334A 4*
15	2 Stroke	2	97-06	0G760300-1B000299	114-5713	174-5721(b)	R98450A10*	154-6770	R84-12334A 4*
18	-	2	80-84	5837437-6443972	114-7452A3	174-6617K 1	R98450A10*	-	R84-88891A1*
18	XD	2	79-87	5837437-0B238463	114-7452A3	174-6617K 1	R98450A10*	-	R84-88891A1*
20	200	2	70-71	2827677-3226957	IN STATOR	174-3996	POINTS	-	-
20	200	2	72-73	3226958-3537530	R336-4516*	174-4469LS 174-4470 HS	POINTS	-	-
20	200	2	73-77	3537531-4403786	114-4911	174-4638	R338-4996A1*	-	414-2770
20	-	2	77-81	4403787-5837436	114-6222	174-6120K1	R74324A3*	-	414-3369
20	XD	2	79-87	5837437-B114230	114-7452A3	174-6617K 1	R98450A10*	-	R84-92436A5*
20	-	2	80-87	5705532-B238463	114-7452K1	174-6617K 1	R98450A10*	-	-
20	-	2	80-87	5705532-B238463	114-7452A3	174-6617K 1	R98450A10*	-	-
20	-	2	88-94	B238464-0G044026	114-7452K1	174-6617K 1	R98450A10*	-	R84-88891A1*
20	-	2	94-96	0G044027-0G437999	114-4952A30	174-6617A17	R98450A10*	154-6770	-
20	Sea Pro	2	96-97	0G438000-0G760299	114-7452K1	174-6617K 1	R98450A10*	154-6770	-

*Premier Services Availability Only **Part Currently Unavailable by CDI Electronic at this time (a) Use 994-4463 (b) Auxillary Charging Stator is Premier Services Only (c) If Linkage 90 Deg., Order 134-6454 (d) If Linkage Straight, Order 134-6452 (e) Order 114-2986K 1 if original had 337-4406 (f) Order 194-1873 if Stator has 2 Yellow Wires (g) Replaces both Rectifier & Regulator

Mercury, Mariner Application Charts

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rec./Reg.	Harness
20	-	2	97-98	0G438000-0G760299	114-4952A30	174-6617A17	R98450A10*	154-6770	R84-92436A5*
20	Comm	2	98-06	0G760300-0T979999	114-5713	174-5721(b)	R98450A10*	154-6770	R84-92436A 9*
20	-	2	98-06	0G760300-0T979999	114-5713	174-5721(b)	R98450A10*	154-6770	R84-92436A 9*
25	XD	2	79-87	5837437-B114230	114-7452A3	174-6617K 1	R98450A10*	-	R84-88891A1*
25	-	2	79-87	5705532-0B238463	114-7452A3	174-6617K 1	R98450A10*	-	-
25	-	2	79-87	5705532-0B238463	114-7452K1	174-6617K 1	R98450A10*	-	-
25	-	2	88-93	0B238464-0G044365	114-7452K1	174-6617K 1	R98450A10*	-	-
25	Sea Pro	2	96-97	0G438000-0G760299	114-7452K1	174-6617K 1	R98450A10*	154-6770	-
25	XD	2	98-06	0G760300-0T979999	114-5713	174-5721(b)	R98450A10*	154-6770	R84-92436A 9*
25	Jet 20	2	94-97	0G044027-0G437999	114-4952A30	174-6617A17	R98450A10*	154-6770	-
25	Elec Str 4 Stk	2	98	0G590000-0G760299	**856482 2	174-2387	-	194-5279	R84-830279A 4*
25	Man. Str. 4 Stk	2	98	0G590000-0G760299	**856482 2	174-2386	-	-	R84-850162A 2*
25	Elec Str 4 Stk	2	99-01	0G760300-0T178499	**8478433A 3	174-2387	-	194-2115K 1	R84-859202T 1*
25	Elec Str 4 Stk	2	2001	0T178500-0T408999	**8478433A 3	174-2387	-	194-2115K 1	R84-859202T 2*
25	Man. Str. 4 Stk	2	2001	0G760300-0G960499	**8478433A 3	174-2386	-	-	R84-850167A 7*
25	Man. Str. 4 Stk	2	2001	0G960500-0T408999	**8478433A 3	174-2386	-	-	R84-850167A 7*
25	Elec Str 4 Stk	2	02-05	0T409000-1B344298	**87843301S	174-2387	-	194-2115K 1	R84-859202T 2*
25	Man. Str. 4 Stk	2	02-05	0T409000-1B344298	**87843301S	174-2386	-	-	R84-859201T 1*
30	Elec Str	2	95-96	0G055314-0G380074	114-7509K1 144-3251A 5	174-2075K 1	134-9021-2	194-5279	R84-824477A 4*
30	Man. Str.	2	95-96	0G055314-0G380074	114-7509K1 144-3251A 5	R398-832074A 5*	134-9021-2	194-5279	R84-824456A 2*
30	Elec Str.	2	96-99	0G380075-0G589999	114-7509K1 144-3251A 6	174-2075K 2	134-9021-2	194-5279	R84-830574A2*
30	Man. Str	2	96-99	0G380075-0G589999	114-7509K1 144-3251A 6	174-2075K 1	134-9021-2	-	R84-854323A 2*
30	Man. Str.	2	98-99	0G590000-0G760299	114-7509	174-2075K 1	134-3960-2	-	R84-824456A 2*
30	Elec Str.	2	98-99	0G590000-0G760299	114-7509	174-2075K 2	134-3960-2	194-5279	R84-824477A 4*
30	Man. Str.	2	99-06	0G760300-0T979999	114-7509	174-2075K 1	134-3960-2	-	R84-854323A 2*
30	Elec Str.	2	99-06	0G760300-0T979999	114-7509	174-2075K 2	134-3960-2	194-5279	R84-854322A 2*
30	Jet	4	89-97	C159200-0G589999	114-5772	174-9710K 1	134-6452(c)	194-5279	414-8672
30	Jet	3	98-01	0G590000-0T408999	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
30	Elec Str 4 Stk	3	02-05	0T178500-0T178499	**87843302S	174-2387	-	194-2115K 1	R84-859197T 3*
30	Man. Str. 4 Stk	3	02-05	0T178500-0T178499	**87843302S	174-2386	-	-	R84-859196T 1*
30	4 Stroke EFI	3	02-05	0T409000-0T800999	-	R398-878143T 3*	-	194-2115K 1	R84-878132T 3*
30	4 Stroke EFI	3	02-05	0T801000-1B344298	-	R398-878143T05*	-	194-2115K 1	R84-878132T04*
35	350	2	68	1960827-2874703	-	**398-2568A 1 Magneto	-	-	R84-34229*
35	-	2	84-86	6445653-0B110788	114-7452A3	174-6617K 1	R92431A 1	154-6770	414-6219A 2
35	-	2	84-86	6445653-0B110788	114-7452K1	174-6617K 1	R92431A 6	-	414-6219A 5
35	-	2	87-89	0B110789-0B393190	114-7452K1	174-6617K 1	R92431A 6	154-6770	414-6219A 5
40	400 Elec Str.	2	70-71	2874704-3336237	R332-4172	174-4424	-	154-6770	414-2770
40	400 Man. Str.	2	70-71	2874704-3336237	R332-4172	174-4424	-	-	-
40	402 Elec Str.	2	72-74	3336258-3859434	114-4911	174-5255	R338-4731A6*	154-6770	414-2770
40	402 Man. Str.	2	72-74	3336258-4117709	114-4911	174-5255	R338-4731A6*	-	-
40	402 Elec Str.	2	75-77	4117710-4860102	114-4911	174-5255	R338-4731A6*	154-6770	414-2770
40	Man. Str.	2	75-81	4117710-5823917	114-4911	174-5255	R338-4731A6*	-	-
40	Elec Str.	2	78-81	4860103-5823917	114-4911	174-5255	R338-4731A6*	154-6770	414-2770

*Premier Services Availability Only **Part Currently Unavailable by CDI Electronics at this time (a) Use 994-4463 (b) Auxillary Charging Stator is Premier Services Only (c) If Linkage 90 Deg., Order 134-6454 (d) If Linkage Straight, Order 134-6452 (e) Order 114-2986K 1 if original had 337-4406 (f) Order 194-1873 if Stator has 2 Yellow Wires (g) Replaces both Rectifier & Regulator

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rec./Reg.	Harness
40	Elec Str.	2	81-84	5823918-6052942	114-7452A3	174-6617K 1	R92431A1*	154-6770	414-6219A 2
40	Elec Str.	2	81-84	6052943-6999999	114-7452A3	174-6617K 1	R92431A1*	154-6770	414-6219A 2
40	Man. Str.	2	81-84	5823918-6999999	114-7452A3	174-6617K 1	R92431A1*	-	-
40	Elec Str.	4	89-91	C159200-D055047	114-5772	174-9710K 1	134-6452(c)	194-5279	414-8672
40	Man. Str.	4	89-91	C159200-D055048	114-5772	174-8778K 1	134-6452(c)	-	-
40	Elec Str.	4	91-97	D055048-OG589999	114-5772	174-9710K 1	134-6452(c)	194-5279	414-8672
40	Elec Str.	2	95-96	OG055314-OG380074	114-7509K 1 144-3251A 5	174-2075K 2	134-9021-2	194-5279	R84-824477A 4*
40	Man. Str.	2	95-96	OG055314-OG380074	114-7509K 1 144-3251A 5	174-2075K 1	134-9021-2	194-5279	R84-824456A 2*
40	Elec Str.	2	96-99	OG380075-OG589999	114-7509 144-3251A 6	174-2075K 2	134-9021-2	194-5279	R84-854322A 2*
40	Man. Str.	2	96-99	OG380075-OG589999	114-7509 144-3251A 6	174-2075K 1	134-9021-2	-	R84-854323A 2*
40	Elec Str.	2	00-05	OG590000-0T999999	114-7509	174-2075K 2	134-3960-2	194-5279	R84-854322A 2*
40	Man. Str.	2	00-05	OG590000-0T999999	114-7509	174-2075K 1	134-3960-2	-	R84-854323A 2*
40	Elec Str.	3	97-05	OG590000-0T999999	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
40	Man. Str.	3	97-05	OG590000-0T999999	114-7509	174-2075K 1	134-4512-3	-	-
40	Elec Str. 4 Stk	3	02-05	0T178500-1B344298	**87843302S	174-2387	-	194-2115K 1	R84-854322A 2*
40	Man. Str. 4 Stk	3	02-05	0T178500-1B344298	**87843302S	174-2386	-	-	R84-854323A 2*
40	Elec Str. 4 Stk	4	02-05	0T178500-0T598999	**878433A 3	174-2387	-	194-2115K 1	R84-857111T 2*
40	Jet	4	89-97	C159200-OG589999	114-5772	174-5454K 1	134-6452(c)	154-6770	414-8672
40	Jet	3	98-01	OG590000-0T408999	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
40	Jet Elec Str.	3	02-05	0T178500-0T979999	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
40	Jet Man Str.	3	02-05	0T178500-0T979999	114-7509	R398-832074A 5*	134-4512-3	-	-
45	Elec Str.	4	81-89	5531630-B393190	114-5772	174-5454K 1	134-6452(c)	154-6770	414-6277
45	Man.Start	4	81-89	5531630-B393190	114-5772	R76314A3	134-6452(c)	-	-
45	Jet	3	91-99	D000750-OG589999	114-9052	174-9710K 1	134-9021-3	194-5279	414-9061
50	500	4	67	2116318-2305100	114-2986	R398-2996	R393-2918A1*	154-6770	414-2770
50	Elec Str.	4	70-75	2858814-4357639	R333-3213*	174-3175 (Red) 174-3176 (Blue)	IGN DRIVER	154-6770	414-2770
50	Elec Str.	4	76-79	4357640-5531629	114-5772	174-5454K 1	134-6452(c)	154-6770	414-3369
50	Man. Str.	4	76-79	4357640-5531629	114-5772	R76314A3*	134-6452(c)	-	-
50	Elec Str.	4	80-85	5531630-A912477	114-5772	174-5454K 1	134-6452(c)	154-6770	414-6277
50	Man. Str.	4	80-85	5531630-A912477	114-5772	R76314A3*	134-6452(c)	-	-
50	-	3	84-90	6428681-D000749	114-7778	174-5454K 1	134-6453	154-6770	414-4614
50	-	3	91-97	D000750-OG589999	114-9052	174-9710K 1	134-9021-3	194-5279	414-9061
50	Man. Str.	3	97-06	OG531301-0T999999	114-7509	R398-832074A 5*	134-4512-3	-	-
50	Elec Str.	3	97-06	OG531301-0T999999	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
50	Jet	3	98-05	OG590000-0T408999	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
50	Elec Str. 4 Stk	4	02-05	0T178500-0T598999	**878433A 3	174-2387	-	194-2115K 1	R84-857111T*
50	EFI 4 Stk	4	2005	0T409000-0T800999	-	R398-878143T 3*	-	194-2115K 1	R84-877804T 3*
50	EFI 4 Stk	4	2006	0T801000-1B344306	-	R398-878143T05*	-	194-2115K 1	-
50	EFI 4 Stk	4	06-07	1B344306-1C050252	-	R398-878143T05*	-	194-2115K 1	-
55	Elec Str.	3	92-97	0D000750-OG589999	114-9052	174-9710K 1	134-9021-3	194-5279	414-9061
55	Man.Start	3	96-97	OG290585-OG589999	114-9052	R398-832074A 5*	134-9021-3	-	-
55	Elec Str.	3	98-07	OG590000-0T980000	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
60	-	3	84-90	6428681-D000749	114-7778	174-5454K 1	134-6453	154-6770	414-4614

*Premier Services Availability Only **Part Currently Unavailable by CDI Electronics at this time (a) Use 994-4463 (b) Auxillary Charging Stator is Premier Services Only (c) If Linkage 90 Deg., Order 134-6454 (d) If Linkage Straight, Order 134-6452 (e) Order 114-2986K 1 if original had 337-4406 (f) Order 194-1873 if Stator has 2 Yellow Wires (g) Replaces both Rectifier & Regulator

Mercury, Mariner Application Charts

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rec./Reg.	Harness
60	-	3	91-97	D000750-OG589999	114-9052	174-9710K 1	134-9021-3	194-5279	414-9061
60	-	3	97-00	OG531301-OG833000	114-7509	174-2075K 1	-	194-5279	414-0220
60	Elec Str.	3	98-07	OG590000-OT980000	114-7509	174-2075K 2	134-4512-3	194-5279	414-0220
60	Elec Str. 4 Stk	4	02-05	OT178500-OT598999	**878433A 3	174-2387	-	194-2115K 1	R84-857111T 2*
60	EFI 4 Stk	4	2005	OT409000-OT800999	-	R398-878143T 3*	-	194-2115K 1	R84-877804T 3*
60	EFI 4 Stk	4	2006	OT801000-1B344306	-	R398-878143T05*	-	194-2115K 1	-
60	EFI 4 Stk	4	06-07	1B344306-1C050252	-	R398-878143T05*	-	194-2115K 1	-
65	650	4	67	2119749-2309310	114-2986	R398-2997*	R393-2918A1*	154-6770	414-2770
65	650	4	68	2309311-2505592	R333-3213*	174-3175 (Red) 174-3176 (Blue)	IGN DRIVER	154-6770	414-2770
65	-	4	69-71	2503993-3293183	114-2986	174-4793	R393-2918A1*	154-6770	414-2770
65	-	3	72-75	3293184-4382056	114-4796	R398-4634*	R332-4797	154-6770	R84-60795*
65	-	3	76	4382057-4571651	114-7778	174-5454K 1	134-6453	154-6770	R84-73204*
65	Jet Elec Str.	3	94-96	D283222-OG760299	114-4953	174-9710K 1	134-9021-3	194-5279	414-1591
65	Jet Man Str.		94-96	OD283222-OG437999	114-4953	R398-9873A33*	134-9021-3	-	-
65	Jet	3	96-06	OG760300-1B000001	114-7509	174-2075K 2	134-4512-3	194-5279	414-0043
70	-	3	77-85	4571652-A730815	114-7778	174-5454K 1	134-6453	154-6770	R84-73204*
70	9 Amp	3	87-89	0A996142-0D283221	114-7778	174-8778K 1	134-9021-3	154-6770	414-1591
70	16 Amp	3	87-89	0A996142-0D283222	114-7778	174-9710K 1	134-9021-3	194-5279	414-1591
75	-	4	84-86	6432901-0C221499	114-5772	174-5454K 1	134-6454(d)	154-6770	414-6233A 2
75	9 Amp	3	87-93	0C221500-0D283221	114-7778	174-8778K 1	134-9021-3	154-6770	414-1591
75	16 Amp	3	87-93	0A996142-0D283221	114-7778	174-9710K 1	134-9021-3	194-5279	414-1591
75	Elec Str.	3	94-96	OD283222-OG437999	114-4953	174-9710K 1	134-9021-3	194-5279	414-1591
75	Man.Str.	3	94-96	OD283222-OG437999	114-4953	R398-9873A33*	134-9021-3	-	-
75	2 Stk.	3	96-06	OG438000-1B000001	114-7509	174-2075K 2	134-4512-3	194-5279	414-0043
80	800	4	69	2559001-2991033	114-2986	174-4793	134-3736	154-6770	414-2770
80	800	4	70	3051041-3052380	114-2986K1	174-4793	134-3736	154-6770	414-2770
80	800	4	70	3052381-3059820	114-2986	174-4793	134-3736	154-6770	414-2770
80	800	4	71	3144219-3192962	114-2986K1	174-4793	134-3736 €	154-6770	414-2770
80	800	4	71-72	3307347-3493912	114-2986	174-4793	134-3736	154-6770	414-2770
80	-	4	78-79	4831999-5582561	114-5772	174-5454K 1	134-6452(c)	154-6770	414-3369
80	-	4	80-83	5582562-6432900	114-5772	174-5454K 1	134-6454	154-6770	414-6233A 2
80	9 Amp	3	87-93	0A996142-0D283221	114-7778	174-8778K 1	134-9021-3	154-6770	414-1591
80	16 Amp	3	87-93	0A996142-0D283221	114-7778	174-9710K 1	134-9021-3	154-6770	414-1591
80	Jet	4	94-96	OD283222-OG437999	114-5772	174-9710K 1	134-9021-4	194-5279	414-0043
80	Jet	4	96-06	OG438000-1B000001	114-7509	174-2075K 2	134-4513-4	194-5279	414-0043
85	850	4	73-75	3493913-4366801	114-2986	174-4793	134-3736	154-6770	414-2770
85	850	4	76-77	4366802-4831998	114-5772	174-5454K 1	134-6452(c)	154-6770	414--3369
90	Inline	6	78-79	4836522-5299505	114-2986	174-4793	134-3736	154-6770	414-2770
90	Inline	6	79	5299506-5595646	114-7778	174-5456	134-6456	154-6770	414-5532
90	Inline	6	79-81	5594657-6026608	114-7778	174-5456	134-6456	154-6770	414-9564
90	Inline	6	82-86	6026609-0B110053	114-7778	174-5456	134-6456	154-6770	R84-96188A 4*
90	Elec Str.	3	87-92	0A996142-0C221999	114-7778	174-8778K 1	134-9021-3	154-6770	414-1591
90	Elec Str.	3	92-94	0C222000-0D283221	114-7778	174-9710K 1	134-9021-3	194-5279	414-1591
90	Elec Str.	3	94-96	OD283222-OG437999	114-4953	174-9710K 1	134-9021-3	194-5279	414-1591
90	Man.Str.	3	94-96	OD283222-OG437999	114-4953	R398-9873A33*	134-9021-3	-	-
90	Elec Str.	3	96-06	OG438000-1B000299	114-7509	174-2075K 2	134-4512-3	194-5279	414-0043

*Premier Services Availability Only **Part Currently Unavailable by CDI Electronics at this time (a) Use 994-4463 (b) Auxillary Charging Stator is Premier Services Only (c) If Linkage 90 Deg., Order 134-6454 (d) If Linkage Straight, Order 134-6452 (e) Order 114-2986K 1 if original had 337-4406 (f) Order 194-1873 if Stator has 2 Yellow Wires (g) Replaces both Rectifier & Regulator

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rec./Reg.	Harness
90	SportJet	3	93-95	0E021000-0E095087	114-4953	174-8778K 1	134-7029-3	194-5279	414-6075
90	SportJet	3	95-96	0E080400-0E145579	114-4953	174-8778K 1	134-7029-3	194-5279	414-6075
95	950 Inline	6	66-67	1869776-2101742	114-2803	R398-2188*	POINTS	-	414-2770
95	950	6	66-67	2101743-2318585	114-2986	R398-2188*	134-3736	154-6770	414-2770
95	XRSprtJet	3	95-97	0E141089-0E315900	114-4953	174-9710K 1	134-7029-3	194-5279	R84-828297A 2*
100	1000 Inline	6	67-69	2641855-3253111	114-2986	R398-3633*	393-2918A1*	154-6770	414-2770
100	-	4	88-93	0B209468-0D283221	114-5772	174-8778K 1	134-9021-4	194-5279	414-3443
100	9 Amp	4	94-96	0D283222-0G437999	114-5772	174-8778K 1	134-9021-4	194-5279	414-3443
100	16 Amp	4	94-96	0D283222-0G437999	114-5772	174-9710K 1	134-9021-4	194-5279	414-3443
100	-	4	96-00	0G438000-0G965520	114-7509	174-2075K 2	134-4513-4	194-5279	414-0043
105	Jet	6	92-95	0D082000-0G201874	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
105	Jet	6	96-00	0G303046-0G760500	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
110	1100 Inline	6	66-67	1962462-2103722	114-2803	R398-2188*	POINTS	R32177A1*	R29999*
110	1101 Inline	6	67	2113898-2314955	114-2986	R398-2188*	134-3736	154-6770	R29999*
115	150 SS Inline	6	70-79	2836019-5314655	114-2986	174-4793	134-3736	154-6770	414-2770
115	Inline	6	79-80	5314656-5600966	114-7778	174-5456	134-6456	154-6770	414-5532
115	Inline	6	80-82	5600967-6051525	114-7778	174-5456	134-6456	154-6770	414-9564
115	Inline	6	82-89	6051526-0C10000	114-7778	174-5456	134-6456	154-6770	R84-96188A 2*
115	9 Amp	4	89-93	0C100000-0D252460	114-5772	174-8778K 1	134-9021-4	194-5279	414-3443
115	16 Amp	4	89-97	0C100000-0G437999	114-5772	174-9710K 1	134-9021-4	194-5279	414-3443
115	-	4	96-06	0G438000-1B000001	114-7509	174-2075K 2	134-4513-4	194-5279	414-0043
120	SportJet	4	95	0E070304-0E141088	114-6866	174-9710K 1	134-7029-4	194-5279	414-6075
120	XRSportJet	4	95-00	0E141089-0E379999	114-7509	174-2075K 2	134-8303-4	194-5279	R84-828297A 2*
125	1250 Inline	6	68-69	2314956-3253111	114-2986	R398-3587*	R393-2918	154-6770	414-2770
125	9 Amp	4	94-96	0D283222-0G437999	114-5772	174-8778K 1	134-9021-4	194-5279	414-3443
125	16 Amp	4	94-96	0D283222-0G437999	114-5772	174-9710K 1	134-9021-4	194-5279	414-3443
125	-	4	96-06	0G438000-1B000001	114-7509	174-2075K 2	134-4513-4	194-5279	414-0043
135	1350 Inline	6	70-71	2839369-3293233	114-2986	174-4793	134-3736	154-6770	414-2770
135	-	6	85-88	0A904646-0C100860	114-7778	174-5456-16	134-6456	154-8825K 1	414-6220A 4
135	-	6	89-90	0C100861-0C239552	114-7778	174-9610K 2	134-6456	194-1873(f)	414-6220A12
135	16 Amp	6	90-91	0C239553-0D081999	114-7778	174-5456-16	134-6456	154-8825K 1	414-6220A 4
135	40 Amp	6	90-91	0C239553-0D081999	114-7778	174-9610K 2	134-6456	194-1873(f)	414-6220A12
135	41 Amp	6	92-95	0D082000-0G201874	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
135	42 Amp	6	96-99	0G303046-0G960499	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
135	-	6	00-05	0G960500-UP	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-857166T 1*
140	1400 Inline	6	72	3293234-3502805	114-2986	174-4793	134-3736	154-6770	414-2770
140	Inline	6	78-79	4855153-5314655	114-2986	174-4793	134-3736	154-6770	414-2770
140	Inline	6	79	5327663-5625107	114-7778	174-5456-16	134-6456	193-5114	414-5532
140	-	6	80-81	5625108-5669999	114-7778	174-5456	134-6456	154-6770	414-9564
140	Jet	6	92-95	0D082000-0G201874	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
140	Jet	6	96-99	0G303046-0G960499	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
140	Jet	6	00-05	0G960500-UP	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-857166T 1*
150	1500 Inline	6	73-77	3502806-4868997	114-2986	174-4793	134-3736	154-6770	414-2770
150	XR2 Mag	6	78-86	04868998-0A904645	114-7778	174-5456	134-6456	154-6770	414-6220A 4
150	-	6	85-88	0A904646-0C100860	114-7778	174-5456-16	134-6456	154-8825K 1 (g)	414-6220A 4
150	-	6	89-90	0C100861-0C239552	114-7778	174-9610K 2	134-6456	194-1873 (f)	414-6220A12

*Premier Services Availability Only **Part Currently Unavailable by CDI Electronics at this time (a) Use 994-4463 (b) Auxillary Charging Stator is Premier Services Only (c) If Linkage 90 Deg., Order 134-6454 (d) If Linkage Straight, Order 134-6452 (e) Order 114-2986K 1 if original had 337-4406 (f) Order 194-1873 if Stator has 2 Yellow Wires (g) Replaces both Rectifier & Regulator

Mercury, Mariner Application Charts

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rec./Reg.	Harness
150	16 Amp	6	90-91	0C239553-0D081999	114-7778	174-5456-16	134-6456	154-8825K 1 (g)	414-6220A 4
150	40 Amp	6	90-91	0C239553-0D081999	114-7778	174-9610K 2	134-6456	194-1873 (f)	414-6220A12
150	40 Ano	6	92-95	0D082000-0G303045	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
150	2 Stk.	6	96-99	0G303046-0G960499	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
150	3 Stk.	6	00-05	0G960500-0T408999	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-857166T 1*
175	Black Max	6	76-79	4301235-5593736	114-7778	174-5456	134-6456	154-6770	414-6220A 4
175	Black Max	6	79-84	5593737-6618750	114-7778	174-5456	134-6456	154-6770	414-6220A 4
175	9 Amp	6	85-88	6618751-0C100860	114-7778	174-5456	134-6456	154-6770	414-6220A 4
175	15 Amp	6	85-88	6618751-0C100860	114-7778	174-5456-16	134-6456	154-8825K 1 (g)	414-6220A 4
175	40 Amp	6	89-90	0C100861-0C239552	114-7778	174-9610K 2	134-6456	194-1873 (f)	414-6220A12
175	16 Amp	6	90-91	0C239553-0D081999	114-7778	174-5456-16	134-6456	154-8825K 1	414-6220A 4
175	40 Amp	6	90-91	0C239553-0D081999	114-7778	174-9610K 2	134-6456	194-1873 (f)	414-6220A12
175	Xri EFI	6	92-95	0D082000-0G303045	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
175	Xri EFI	6	96-00	0G303046-0G840500	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
175	2 Stk.	6	96-99	0G303046-0G960499	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
175	3 Stk.	6	00-05	0G960500-0T408999	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-857166T 1*
175	XR2 Sp. Jet	6	97-05	0E151580-0E433133	114-4953-32	174-9873-16	134-6456-15	194-5279	R84-832102A 2*
200	Black Max	6	78-79	4839034-5363917	114-7778	174-5456	134-6456	154-6770	414-6220A 4
200	Black Max	6	79-81	5363918-6073191	114-7778	174-5456	134-6456	154-6770	R84-87266A1*
200	15 Amp	6	82-90	6073192-0C239553	114-7778	174-5456-16	134-6456	194-8825K 1(g)	414-6220A 4
200	16 Amp	6	85-90	6625221-0C239553	114-7778	174-5456-16	134-6456	194-8825K 1(g)	414-6220A 4
200	Xri 40 Amp	6	89-91	0C100861-0G303045	114-7778	174-9610K 2	134-6456	194-1873 (f)	414-6220A 12
200	16 Amp	6	89-91	0D082000-0G201874	114-7778	174-5456-16	134-6456	194-8825K 1	414-6220A16
200	40 Amp	6	89-91	0G201875-0G303045	114-7778	174-9610K 2	134-6456	194-1873(f)	R84-826730A 4*
200	2 Stk.	6	92-00	0G303046-0G960499	114-7778	174-9610K 2	134-6456	194-5279	R84-826730A 4*
200	2 Stk.	6	00-05	0G960500-1B226999	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-857166T 1*
200	2.5L EFI	6	92-99	0D082000-0G840500	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
200	EFI	6	00-05	0G960500-0T408999	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-857166T 1*
210	Sp Jet	6	97-99	0E370318-0E433133	114-4953-32	174-9873-16	134-6456-15	194-5279	R84-832102A 2*
220	-	6	87-88	0B117316-0C100860	114-7778	174-5456-16	134-6456	194-8825K 1(g)	R84-92432A 6*
225	-	6	81-93	5628028-0D280812	114-7778	174-5456-16	134-6456	194-8825K 1	-
225	2.5L EFI	6	95-00	0D935638-0G569900	114-7778	174-9610K 2	134-6456	194-5279	414-6220A16
225	3.0L	6	93-94	0D280813-0G129221	114-7509K1	R821935A 3*	-	Alternator	R84-825433A 7*
225	3.0L	6	94-95	0G129222-0G303045	114-7509K1	R821935A 5*	-	Alternator	-
225	3.0L	6	96-01	0G303046-0T408999	114-7509	R821935A 5*	-	Alternator	-
240	Sp Jet	6	00-05	0E373939-0E406399	114-7509	R398-858404T*	134-6456-18	194-2115K 1	R84-877614A 2*
250	3.0L	6	94-95	0G129222-0G303045	114-7509K1	R821935A 5*	-	Alternator	-
250	3.0L	6	96-00	0G303046-0G840500	114-7509	R821935A 5*	-	Alternator	-
250	XB 3.0L	6	00-02	0G980600-0T408999	114-7509	R821935A 5*	-	Alternator	R84-825433A11*
300	ProMax	6	98-01	0G980600-0T408999	114-7509	R821935A 5*	-	Alternator	R84-825433A11*

*Premier Services Availability Only **Part Currently Unavailable by CDI Electronics at this time (a) Use 994-4463 (b) Auxillary Charging Stator is Premier Services Only (c) If Linkage 90 Deg., Order 134-6454 (d) If Linkage Straight, Order 134-6452 (e) Order 114-2986K 1 if original had 337-4406 (f) Order 194-1873 if Stator has 2 Yellow Wires (g) Replaces both Rectifier & Regulator